

## Combining Lights



It is possible to combine multiple lights together if required.

Slide the light into one of the three mounting points on the top or the sides of the light. Then secure in place by tightening the locking disc. (A)



## Specifications

LED	120pcs white LEDs with high brightness
Brightness	1300lx /50cm/20" (325lx /1m) /39"
ISO100 50cm	f 8 / 1/8 S
Beam angle	60 degree
Colour Temperature	5600 ± 600K
Continuous working hours	Approx. 3 hours
Battery lifetime	Charge for approx. 500 times
Output power	7.5W
Chargeable voltage	AC 100-240V
Built-in Lithium battery	Rechargeable, 3400m AH, 3.7V
Battery charge display	4 levels
Dimension	94 x 81 x 31mm
Weight	189g / 6.6oz
Hot shoe mount	Up / Left / Right 3pcs
Accessory	Camera bracket

## On Camera LED Light Guide



# Components



A	Charger
B	120 LED Lamp Light
C	Diffusion Filter
D	Camera Light Mount



A	Charge Socket
B	Battery level indicator
C	On/Off Switch
D	Dimmer Control

# Charging



1. Charge the light for at least 12 hours before use.

2. Connect the charger to the light using the DC Input socket. (A)



# Controls



You can monitor the battery level by pressing the Test button marked T.

The brightness can be controlled with the brightness slider.

Switch the unit on and off using the On/Off switch.



The light can be mounted directly to your camera or the Camera Light Mount. Secure in place by using the locking disc. (A)



Install the Diffusion Filter if required. Slide the filter into the guides to secure it in place.